TMC SPECIFICATION NO. S- 398

TMC SPECIFICATION NO. S- 398

TMLE: RSM-2 to RSM-3 MODIFICATION KIT JOB (FV, A
APPROVED P. FK (See ML-5-398) MODIFICATION KIT, TMC NO. 145

I. PURPOSE:

To describe the procedure for modifying the RSM-2 to become an RSM-3.

A. Changes Involved:

1. Replacing Transformer TF-126 (T3) with Transformer TF-194.

II. PROCEDURE:

- A. Changing Transformer:
 - 1. Unsolder all leads to TF-126 (T3) and keep a note of which color lead goes to which terminal.
 - 2. Remove transformer TF-126, and keep all mounting hardware.
 - 3. Replace with TF-194, using existing mount-ing hardware.
 - 4. Solder all leads to the same number terminals as they were on the old transformer, with the exception of the lead that went to terminal No. 2. This lead may go to terminal No. 2A, 2B, 2C, 3A, 3B on the new transformer, depending upon the line voltage.

REVI:	MOI	SHEET	•	THE TECHNICAL MATERIEL CORP. MAMARONECK NEW YORK	S-398		
MODEL	RSM-	.3		PROJECT NO			
DATE	REV.	PAGE	EMN#	DESCRIPTION		снк.	APP.
9/12/62		1		On Title add: P/O KIT-145			16
							<u> </u>
							ļ
							<u> </u>
					,		
						_	ļ
							ļ
						_	
ļ							<u> </u>
		ļ					<u> </u>
							
							
			ļ				ļ
ļ							-
			<u> </u>				1
							
			<u> </u>				
							
			<u> </u>				
 		-					
-		_	 				1
							<u> </u>
	1	1	1	1		I	1